
SARGENT° 1431 (OT or HT) B PULL SIDE TRACK APPLICATION INSTALLATION INSTRUCTIONS

CAUTION: FAILURE TO INSTALL OR ADJUST PROPERLY MAY RESULT IN INJURY OR DAMAGE.

FOR ASSISTANCE, CALL SARGENT AT 1-800-727-5477



Pre-drill - 3/32" holes for self tapping screws or #16 drill for #12-24 tap for machine screws

SARGENT Manufacturing Company 2007

With provided fastener, secure closer body to door with power adjustment away from hinge

FRAME

DOOR STOP

Power Adjustment

DRILL 3/8" DIA. HOLE
FOR MORTISE NUT BODY


FOR MORTISE NUT BODY


DRILL 1/4" DIA. HOLE
FOR MORTISE NUT BODY

DOOR


Use optional mortise nuts when through-bolting

A7193E






Accessories information



FINAL ADJUSTMENT AND REGULATING PROCEDURES

Regulate door speed, latching speed and backcheck. Recommended closing time greater than 6 seconds.


If backcheck is required, adjust for slight cushioning effect. *Auxiliary door stop required. Use 1/8" hex wrench and adjust valves as needed.




*If adjustments are ineffective, check indexing as shown in step 3 and check templating

Adjust power to minimum required to reliably close and latch door

NUMBER OF TURNS OF SPRING POWER ADJUSTING NUT	
DOOR WIDTH (INCHES)	ADJUSTMENTS
24-30	Turn nut 1-3 🔍
30-36	Factory Set
36-42	Turn nut 1-3
42-48	4-6



Adjusting door to close due to high draft conditions may exceed ADA standards. Consult local ordinances when fire doors are involved.




Adjustments for "B" and "H" option

"B" option

6


Bumper assists backcheck in cushioning the opening for door. It is not intended to replace an auxiliary door stop.

To change bumper stop location: Remove mounting screw and relocate bumper stop at desired position



"H" option

The **holder** device is set for 95° door holding position at the factory. Tension is set at the lightest setting.




To increase holding tension: Remove tensioner mounting screw and move tension adjuster toward holder slide by using either of the two hole locations To change hold open position: Remove holder and tensioner mounting screw, slide holder & tensioner to desired

position and reinstall screws

SARGENT[®] A7193E

3

SARGENT Manufacturing Company 2007



A7188 B

RIGHT HAND DOOR SHOWN, LEFT HAND OPPOSITE.